







B&N CONTAINERIZED GENERATORS

Range: 20 -100 kVA

STANDARD SCOPE OF SUPPLY:

Diesel engine (EU Stage IIIA) Mecc Alte alternator Residential exhaust silencer Exhaust flexible section Large fuel tank with contents gauge Bunding for the fuel tank Anti-vibration mountings Autostart digital control panel (Deep Sea Electronics) AC output circuit breaker with over-current protection Starter battery and leads Air cleaner Oil and fuel filters Fuel/water seperator Low engine oil pressure protection High engine temperature protection Single-bearing 4-pole brushless alternator Operators handbook Electrical diagrams

OPTIONAL:

Engine mounted sump pump Automatic mains failure set Mains operated battery charger Mains operated coolant heater Distribution board Single phase

Made in Europe !

ALWAYS MOVING FORWARD

WIDE RANGE OF PRODUCTS

Confidence by delivering good quality and service is where Brinkmann & Niemeijer stands. B&N supplies Generators for Marine, Agriculture, Government, Contracting and the automotive sector. Please contact us for customized products or bespoke projects.









	Model	Prime Power	Engine	Alternator	Dimensions (cm)			Weight*	Fuel Tank
		kVA / KW	Model	Model	L	W	Н	Kg	Capacity (Ltr)
	LG3P20M/EC	20/16	404D-20G	ECP28-VL/4	244	220	215	3180	900
	LG3Y40M/EC	40/32	4TNV98T-ZGGE	ECP32-35/4	299	244	259	3200	1480
1	LG3P60M/EC	60/48	1104D-44TG2	ECP32-3L/4	299	244	259	3490	1480
	LG3P100M/EC	100/80	1104D-E44TAG2	ECP34-2S/4	299	244	259	3590	1480

- * Dry weight without fuel
- All models based on 50 Hz, 400/230V, 3 phase

- Larger models on request (up to 2.200 kVA)

ALWAYS MOVING FORWARD

LG.12.0118.01 (ENG

www.bnmotoren.nl Engelenburgstraat 45, 7391 AM TWELLO T. 0571-276 900, F 0571-276 800, info@bnmotoren.nl

